


Last information update: July 2025



Accessory code

PF05: Floor box complete with 60W power supply - PUSH DIM -

Technical description

Floor box complete with 60W power supply. Power cable with Schuko plug L=2000mm and floor-cabled Push-dim button that switches the Libera products connected to the line on and off and adjusts their intensity. Electrified power supply end cap that includes a power cable L=1500mm. Painted extruded aluminium box with brass truncated cone part.

Installation

Floor-mounted

Colour

White (01) | Black (04) | Titanium (N8) | Sapphire blue (N9)

Weight (Kg)

3.25

Complies with EN60598-1 and pertinent regulations



Technical data

Frequency [Hz]:	0/50/60	Overvoltage protection:	2kV Common mode & 1kV Differential mode
Inrush current:	39 A / 187 µs	Control:	Push Dim
Maximum number of LED power supply units of this type per miniature circuit breaker:	B10A: 9 power supply units B16A: 15 power supply units C10A: 15 power supply units C16A: 25 power supply units		