

---

## Emergency kit

Design iGuzzini

iGuzzini

Last information update: November 2023



### Accessory code

MY21: Emergency kit

---

### Technical description

The kit includes the power supply + inverter + Ni-Mh battery. The recessed fitting connected to the kit is assigned to the emergency mode operation. 12-hour recharging for emergency autonomy of 1.5 hours / 24-hour recharging for emergency autonomy of 3 hours. The warning LED included must be positioned close to the emergency recessed opening. Further technical specifications on the emergency mode can be found in the instructions.

---

### Installation

Positioning the emergency unit in the recessed opening preparation hole. The warning LED needs a  $\varnothing$  12 mm preparation hole (for the correct distances see the instructions).

---

### Colour

Indeterminate (00)

---

### Weight (Kg)

0.75

---

### Wiring

Connections with specific connectors L + N / Le + Ne (emergency line) - connection of the warning LED, battery and recessed light with fast coupling terminals.

Complies with EN60598-1 and pertinent regulations

**ERL**