iGuzzini

Last information update: December 2024

Product configuration: BU22

BU22: Wall/ceiling mounted, ø110mm luminaire with an electronic transformer - Warm White - 180° blade effect



ø110

89



 $BU22: Wall/ceiling \ mounted, \ \texttt{ø110} mm \ luminaire \ with \ an \ electronic \ transformer \ - \ Warm \ White \ - \ 180^\circ \ blade \ effect$

Technical description

Wall and ceiling-mounted luminaire, designed for use with LED lamps and a patented, 180° blade effect optic. The product consists of a support base and screen. The base is made of phosphocromatization treated, die-cast aluminium, with a double base coat and passivation at 120°C. It is coated with liquid acrylic paint, cured at 150 °C to guarantee a high level of weather and UV ray resistance. The optic is made of methacrylate and fixed to the body via a zamak cover. All the screws used are made of A2 stainless steel.

Installation

Wall and ceiling mounted by means of a stainless steel wall fixture plate.

Colour

White (01) | Grey (15)

Weight (Kg) 0.56

Mounting

wall surface|ceiling surface



Equipped with electronic ballast.

Notes

Complete with lamp. On request available with LED cool white (6700K), red, green and amber.



Technical data			
Im system:	103	Life Time LED 2:	100,000h - L80 - B10 (Ta 40°C)
W system:	3.9	Lamp code:	LED
Im source:	410	Number of lamps for optical	1
W source:	2.9	assembly:	
Luminous efficiency (Im/W,	26.3	ZVEI Code:	LED
real value):		Number of optical	1
Im in emergency mode:	-	assemblies:	
Total light flux at or above an angle of 90° [Lm]:	1	Intervallo temperatura ambiente:	from -30°C to 50°C.
Light Output Ratio (L.O.R.) [%]:	25	Lifetime of product at ambient operating	≥ 50.000h Ta=40°C
CRI (minimum):	80	temperature:	
Colour temperature [K]:	3000	Power factor:	See installation instructions
MacAdam Step:	3	Inrush current:	20 A / 170 μs
Life Time LED 1:	100,000h - L80 - B10 (Ta 25°C)	Maximum number of luminaires of this type per miniature circuit breaker:	B10A: 31 luminaires B16A: 50 luminaires C10A: 52 luminaires C16A: 85 luminaires
		Overvoltage protection:	2kV Common mode & 2kV Differential mode



