

## Light Shed 14

Design iGuzzini

iGuzzini

Last information update: July 2025



### Accessory code

X669: BLE module - 2.4 GHz - Complete with Bluetooth interface - For Light Shed 14

### Technical description

Module complete with interface compatible with the Bluetooth Casambi system. The integrated interface allows n.20 DALI drivers to be controlled on Light Shed 14 luminaires in broadcast mode (or 8 drivers single group). Devices can be programmed, enabled and connected via the Casambi app available on Apple Store and Google Play Store. Frequency and protocol: 2.4 GHz Bluetooth Low Energy. OTA (over the air) update via app. Integrated beacon that can be activated via an app (iBeacon protocol).

### Installation

Installation on pendant modules: only at the end opposite to the power supply base and also in the intermediate position.  
Installation on ceiling-mounted modules: only at the end opposite to the power supply.

To position the module correctly and the connection accessories required, see the instruction sheet. Distance of the interface module from other interface modules max 8 m and between interface module and smartphones max 20 m - Line of sight(\*)

### Colour

White (01) | Black (04)

### Weight (Kg)

0.34

### Wiring

The module is powered by the wiring inside the Light Shed 14 it is connected to.

### Notes

(\*) Maximum radius of action: the maximum distance depends on the presence of fixed obstacles like concrete walls or metal panels.

Complies with EN60598-1 and pertinent regulations



IP20



### Technical data

Control: Casambi