

DALI IP20 35W constant current power supply - for 3 Crystal recessed luminaires

Last information update: January 2025



Accessory code

PD78: DALI IP20 35W constant current power supply - for 3 Crystal recessed luminaires

Technical description

DALI 35W dimmable constant current electronic power supply.  
Input Vin=220÷240 Vac 50÷60Hz.  
SELV output.  
The product features include common mode and differential mode overvoltage protection, short circuit protection, overcurrent and overtemperature protection.

Installation

Compatible with opening for Crystal recessed fitting assembly.

| Colour  | Weight (Kg) | Dimension (mm) (*) |
|---|-------------|--------------------|
| Indeterminate (00)  | 0.15        | 169x67x30          |
| * The dimensions may change according to production requirements to ensure that performance levels and installation methods are observed. |             |                    |

Wiring

The power supply is fitted with a cable and quick-coupling connector for facilitating a direct connection to the splitter accessory required for the junction.  
Cable clamp on primary and secondary.

Notes

SELV

Complies with EN60598-1 and pertinent regulations



Technical data

|                   |     |          |        |
|-------------------|-----|----------|--------|
| Current out [mA]: | 930 | Control: | DALI-2 |
|-------------------|-----|----------|--------|