

Constant current power supply unit on-off IP20 10W - VIN = 110-240VAC 50/60Hz

Design iGuzzini

iGuzzini

Last information update: September 2023



Accessory code

PA81: Constant current power supply unit on-off IP20 10W - VIN = 110-240VAC 50/60Hz

Technical description

Electronic ballast 10W - Direct Current 250 mA operation.

Installation

Remote installation.

Colour

Indeterminate (00)

Dimension (mm) (*)

115x34x19

* The dimensions may change according to production requirements to ensure that performance levels and installation methods are observed.

Wiring

The ballast includes a cable and quick-coupling connector to make it easier to connect up to the recessed fitting.

Complies with EN60598-1 and pertinent regulations



Technical data

Frequency [Hz]: 50/60

Current out [mA]: 200

Inrush current: 5 A / 50 µs

Maximum number of LED power supply units of this type per miniature circuit breaker:

B10A: 31 power supply units
B16A: 50 power supply units
C10A: 52 power supply units
C16A: 85 power supply units

Overvoltage protection:

4kV Common mode & 2kV Differential mode