

Constant current power supply unit 1-10V IP20 35W - VIN = 220-240VAC 50/60Hz Ø17

Design iGuzzini

iGuzzini

Last information update: July 2024



Accessory code

MY04: Constant current power supply unit 1-10V IP20 35W - VIN = 220-240VAC 50/60Hz Ø17

Technical description

Dimmable 1-10V electronic ballast - 500 mA constant current operation. Protection devices: mains overvoltage - thermal - overloads.

Installation

remote installation - including securing slots with screws.

Colour

Indeterminate (00)

Weight (Kg)

0.09

Dimension (mm) (*)

124x79x22

* The dimensions may change according to production requirements to ensure that performance levels and installation methods are observed.

Wiring

500 mA for Ø17 Laser - min 2 - max 20 used. Cables secured with terminals.

Complies with EN60598-1 and pertinent regulations



Technical data

Frequency [Hz]: 0/50/60

Current out [mA]: 500

Inrush current: 20 A / 400 µs

Maximum number of LED power supply units of this type per miniature circuit breaker:

B10A: 9 power supply units
B16A: 15 power supply units
C10A: 15 power supply units
C16A: 25 power supply units

Overvoltage protection: 4kV Common mode & 4kV Differential mode