

Last information update: June 2021



Product code

MI50: I/O module DR-N 3DIM 1-10V **Attention! Code no longer in production**

Technical description

Control of devices with 1-10V interface (controllable electronic ballasts, electronic transformers, etc.). Three analogue outputs (1-10V) for dimming and three relay outputs (NO contact, 16 A) for on/off function. Load current (analogue output): max. 100 mA. Voltage drop detection. Wire clamp screw terminals. Power supply voltage: 24V dc. Switch for manual control of relay contact. Screw terminals. Software application for dimming the lighting, including timers, priority control and configurable behaviour in the event of voltage recovery or bus reset. Application also allows constant control of the lighting and scenes according to the LonMark "Lamp actuator (3040)" profile, "Constant Light Controller (3050)" and "Scene Controller (3251)"

Colour
Indeterminate (00)

Weight (Kg)
0.3

Complies with EN60598-1 and pertinent regulations

